




## Compatible Halogen Transformer List

**MEGAMAN® LED MR16 4W  
ER0604-FL***Halogen Transformer 220-240V*

Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
3E	TFM-60A	60	4
Actec	MINI60	20-60	3
Anchorn	AET-3502R1	35-150	4
Andawo	MR-128	20-50	4
ATCO	LVL27-2	50	4
BLV	456000	0-50	4
Cata Plus	CP-2551	22-60	4
Click	TR060	20-60	4
Dura	DELT12060P	20-60	4
Dura	DELT12105M	35-150	4
ELT	TR 5/23-01-SC	50	4
EMC	ET105	35-105	4
GIRA	Tronic-Trafo 0366 00	20-70	3
GIRA	Tronic-Trafo 0378 00	20-105	4
Halolite	HA-S60TA	20-60	3
HEP	LMV12W12 UNI	12	4
HEP	TB60B 10-60W	10-60	4
Kengo	DET60S	10-60	4
Lite Beetle	LET 105/240LB	35-105	4
Lite-Tech	SY1507	20-60	1
Lival	Pico Wolf 70	70	3
Lucci	TB60L 240 10 - 60W	10 - 60	4
Meek	ET-60W	60	4
Niko	320-00002	50	4
Niko	320-00106	20-70	4
Nobile	EN-110D2	35-110	4
NVC	AET-60A	20-60	2



Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
NVC	ET50S	50	4
NVC	ET60E	20-60	4
Osram	ET-REDBACK 60VA/230-240	20-60	4
Osram	HALOTRONIC HTM 105/230-240	35-105	4
Osram	HALOTRONIC HTM 70/230-240	20-70	4
Philips	EHC075 S	20-75	4
Philips	EHC250 F	35-60	1
Philips	ET-E 60 220-240	20-60	4
Philips	ET-S 150 220-240	50-150	4
Philips	ET-S 60 220-240	20-60	2
QLT	W60	20-60	2
Robus	LDT150N	35-150	3
Robus	RM70DN	70	4
Self	SET70F-2	20-70	4
Self	SET70R	20-70	4
Shark	Power Transformer 220V 12V 55W	55	4
Skytronic	VWY-006	20	4
TAO	SET150-2	50-150	4
TAO	TET-E60I	60	4
TCI	Pico Wolf 105	105	2
Thorn	ICE742, ECT90-220/12V	50	4
Toroidal Technologies	TRI-50-C	50	4
Tridonic	TE-0050 C101	20-50	1
Tridonic	TE-0070 C101	20-70	1
Tridonic	TE-0105 S003	105	2
Tridonic ATCO	VIPER 22176070	60	4
Ushio Group	456001	0-60	4
Wei Tai	Electronic Transformer	60	4



## Compatible Halogen Transformer List

**MEGAMAN® LED MR16 6W  
ER1006-35H24D and ER1006-35H36D***Halogen Transformer 220-240V*

Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
3E	TFM-60A	60	3
Actec	MINI60	20-60	1
Anchorn	AET-3502R1	35-150	3
Andawo	MR-128	20-50	3
Atom	Tiger	20-60	3
Click	TR060	20-60	2
Dura	DELT12060P	20-60	3
Dura	DELT12105M	35-150	3
ELT	TR 5/23-01-SC	50	3
ERC	Trael02	20-60	3
Halolite	HA-S60TA	20-60	3
HEP	LMV12W12 UNI	12	3
Horoz	HL 371	105	3
Kengo	DET60S	10-60	1
Kengo	KET105	35-105	3
Layrton	TRI-50 ENC	50	3
Lival	Pico Wolf 70	70	2
Lucci	TB60L 240 10-60W	10-60	3
Meek	ET-60W	60	3
Niko	320-00002	50	3
Nobile	EN-110D2	35-110	3
NVC	ET60E	20-60	3
Osram	ET-PARROT 105/240 I	35-105	3
Osram	ET-PARROT 70/220-240 I	20-70	2
Osram	ET-REDBACK 60VA/230-240	20-60	3
Osram	ET-Z 60/220-240	20-60	3
Pashaught	CS1402	35-105	3



Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
Philips	EHC250 F	35-60	3
Philips	ET-E 60 220-240	20-60	3
Philips	ET-S 60 220-240	20-60	2
Robus	RM70DN	70	3
Self	SET70F-2	20-70	3
Skytronic	VWY-006	20	3
TAO	SET150-2	50-150	3
TCI	Pico Wolf 105	105	1
TCI	Pico Wolf 60	10-60	1
Tridonic ATCO	VIPER 22176070	60	2
Ushio Group	456001	0-60	3



## Compatible Halogen Transformer List

**MEGAMAN® LED AR111 11W  
ER1111-50H24D, ER1211-50H08D and  
ER1311-50H45D***Halogen Transformer 220-240V*

Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
3E	TFM-60A	60	2
Actec	MINI60	20-60	2
Anchorn	AET-3502R1	35-150	2
Andawo	MR-128	20-50	2
Atom	Tiger	20-60	2
Cata Plus	CP-2551	22-60	2
Click	TR060	20-60	2
Dura	DELT12060P	20-60	2
Dura	DELT12105M	35-150	2
ELT	TCE 5/23-E	50	2
ELT	TR 5/23-01-SC	50	2
EMC	ET105	35-105	2
ERC	Trael02	20-60	2
Flash Light	HA-105	35-105	2
Flash Light	HA-60	20-60	2
GIRA	Tronic-Trafo 0371 00	20-105	2
GIRA	Tronic-Trafo 0378 00	20-105	2
Halolite	HA-S105	35-105	2
Halolite	HA-S60TA	20-60	2
Halolite	HA-SE60	20-60	2
Horoz	HL 371	105	2
Kengo	DET60S	10-60	2
Kengo	KET105	35-105	2
Layrton	TRI-50 ENC	50	2
Lite Beetle	LET 105/240LB	35-105	2
Lival	Pico Wolf 60	60	2
Lival	Pico Wolf 70	70	2



Manufacturer	Model No.	Wattage (W)	Max. number of LED Lamp(s) compatible*
Lucci	TB60L 240 10-60W	10-60	2
Meek	ET-60W	60	2
Niko	320-00002	50	2
Niko	320-00106	20-70	2
Nobile	EN-110D2	35-110	2
NVC	ET60E	20-60	2
Osram	ET-PARROT 105/240 I	35-105	2
Osram	ET-PARROT 70/220-240 I	20-70	2
Osram	ET-REDBACK 60VA/230-240	20-60	2
Osram	ET-Z 60/220-240	20-60	2
Osram	HALOTRONIC HTM 105/230-240	35-105	2
Pashaught	CS1402	35-105	2
Philips	EHC250 F	35-60	2
Philips	ET-E 60 220-240	20-60	2
Philips	ET-S 60 220-240	20-60	2
QLT	T105K	35-105	2
QLT	W60	20-60	2
Robus	LDT150N	35-150	2
Robus	RM70DN	70	2
Self	SET70F-2	20-70	2
Self	SET70R	20-70	2
Skytronic	VWY-006	20	2
SLI Sylvania	Lumitronic IOS	35-105	2
TAO	SET150-2	50-150	2
TAO	TET-E60I	60	2
TCI	Pico Wolf 105	105	2
TCI	Pico Wolf 60	10-60	2
TCI	SHARK60	10-60	2
Tridonic	TE-0070 C101	20-70	2
Tridonic	TE-0105 C101	35-105	2
Tridonic	TE-0105 S003	105	2
Tridonic ATCO	Possum 89400085	60	2
Tridonic ATCO	Speedy TE-0050 C101	20-50	2



<b>Manufacturer</b>	<b>Model No.</b>	<b>Wattage (W)</b>	<b>Max. number of LED Lamp(s) compatible*</b>
Tridonic ATCO	VIPER 22176070	60	2
Ushio Group	456001	0-60	2

Remarks: \*The maximum number of LED lamps compatible is depend on the transformer performance.  
Copyright © MEGAMAN<sup>®</sup> 2011. All rights reserved.  
All information contained in this publication is correct at time of update and subject to change without prior notice.  
All other trademarks mentioned are the property of their respective owners.